

## Initiate Update Procedure Desk 3500

1. Make sure the device is plugged into a power supply
2. Settle any open batches
3. From the home screen press the **Admin Key**
4. The terminal should display **Admin Mode**
5. Press **Admin Mode**
6. Enter the Admin PW (**16G36120**)
7. The Terminal will display multiple menus
8. **Scroll down** using the Up and Down Keys
9. Choose **Tetra Admin**
10. Select **1-Download Application**
11. The Terminal will display **1-configure download** and **2-start download**
12. Select **2-start download**
13. The terminal should start downloading
14. If the terminal displays **enter package name** just **press enter**
15. Terminal will download
16. After the download is complete the terminal will **reboot** and print a receipt stating **parameter data update succeeded**

## Initiate Update Procedure Desk 5000

1. Make sure the device is plugged into a power supply
2. Settle any open batches
3. From the home screen press the **Admin Key**
4. **Swipe** the screen to the **left**
5. The terminal should display **Admin Mode**
6. Press **Admin Mode**
7. Enter the Admin PW (**16G36120**)
8. Terminal will display multiple menus
9. Choose **Tetra Admin**
10. Select **1-Download Application**
11. Terminal will display **1-configure download** and **2-start download**
12. Select **2-start download**
13. The terminal should start downloading
14. If the terminal displays **enter package name** just **press enter**
15. Terminal will download
16. After the download is complete the terminal will **reboot** and print a receipt stating **parameter data update succeeded**

# Initiate Update Procedure Move 5000

1. Make sure the device is on its docking station and plugged into a power supply
2. Settle any open batches
3. From the home screen press the **Admin Key**
4. **Swipe** the screen to the **left**
5. The terminal should display **Admin Mode**
6. Press **Admin Mode**
7. Enter the Admin PW (**16G36120**)
8. Terminal will display multiple menus
9. Choose **Tetra Admin**
10. Select **1-Download Application**
11. Terminal will display **1-configure download** and **2-start download**
12. Select **2-start download**
13. The terminal should start downloading
14. If the terminal displays **enter package name** just **press enter**
15. Terminal will download
16. After the download is complete the terminal will **reboot** and print a receipt stating **parameter data update succeeded**